



OPTICAL TRANSCEIVER TEST REPORT

Tested by: Doubt.Zheng | Date: 2022.06.03

1. Test Purpose

Test objects: SFP-1G-CW10-1470, Through the corresponding tests, the test parameters conform to the relevant industry standards, and the test transceivers can be used normally in Extreme brand equipment, laying the foundation for the subsequent cooperation with customers.

2. Test items

Test items		Test details
Compatibility Testing	Connectivity testing	The transceiver can connect both ends of the device normally, and the device port status is up.
	Parameter testing	The transceiver PN, VN, SN, and DDM information read by the device is consistent with the module tag description.

3. Test environment

3.1. Test samples

Vendor Name	Part Number	Serial Number	Transceiver Description
NADDOD	SFP-1G-CW10-1470	ACS22060700480	1000BASE-CWDM SFP 1270~1610nm 10km DOM LC SMF Transceiver Module
NADDOD	SFP-1G-CW10-1470	ACS22060700481	1000BASE-CWDM SFP 1270~1610nm 10km DOM LC SMF Transceiver Module

3.2. Test equipment

Equipment Brand	Equipment Model	Software version (running)
Cisco	N9K-C93180YC-EX	NXOS: version 9.2(3)

4. Test data

4.1. Connectivity testing

Test Method	<ol style="list-style-type: none"> check whether the device status is normal.; Check whether the port device port LED is green; (individual brand port LED is yellow or white) check whether the device port is normally linked up;
-------------	--

4. Check whether the device port rate is up to standard.

Test Data

```

switch# sh inv
NAME: "Chassis", DESCR: "Nexus9000 93180YC-EX chassis"
PID: N9K-C93180YC-EX , VID: V01 , SN: FDO21192HKE

NAME: "Slot 1", DESCR: "48x10/25G + 6x40/100G Ethernet Module"
PID: N9K-C93180YC-EX , VID: V01 , SN: FDO21192HKE

NAME: "Power Supply 1", DESCR: "Nexus9000 93180YC-EX chassis Power Supply"
PID: NXA-PAC-650W-PE , VID: V02 , SN: LIT21182CKL

NAME: "Power Supply 2", DESCR: "Nexus9000 93180YC-EX chassis Power Supply"
PID: NXA-PAC-650W-PE , VID: V02 , SN: LIT21182G55

NAME: "Fan 1", DESCR: "Nexus9000 93180YC-EX chassis Fan Module"
PID: NXA-FAN-30CFM-F , VID: V01 , SN: N/A

NAME: "Fan 2", DESCR: "Nexus9000 93180YC-EX chassis Fan Module"
PID: NXA-FAN-30CFM-F , VID: V01 , SN: N/A

NAME: "Fan 3", DESCR: "Nexus9000 93180YC-EX chassis Fan Module"
PID: NXA-FAN-30CFM-F , VID: V01 , SN: N/A

NAME: "Fan 4", DESCR: "Nexus9000 93180YC-EX chassis Fan Module"
PID: NXA-FAN-30CFM-F , VID: V01 , SN: N/A

switch# show interface status

-----
Port          Name          Status      Vlan      Duplex  Speed  Type
-----
mgmt0         --            notconnec  routed   auto    auto   --
-----

Port          Name          Status      Vlan      Duplex  Speed  Type
-----
Eth1/18      --            xcvrAbsen  routed   auto    auto   --
Eth1/19      --            connected  routed   full    1000   CWDM-1470
Eth1/20      --            connected  routed   full    1000   CWDM-1470

```

Test Situation	Equipment model	N9K-C93180YC-EX	
	Port Number	Eth1/19	Eth1/20
	Port Status	connected	connected
	Port Link Rate	1000	1000
Test Conclusion	After testing, the above transceivers are normally connected on N9K-C93180YC-EX, the device port LEDs at both ends are always on white, the link is linkup.		
Remarks			

4.2. Parameter Testing

Test Method	<ol style="list-style-type: none"> check whether the basic information such as module manufacturer name, model name and serial number is correct. check whether the module transmission distance, wavelength, type and other key parameters are correct. check whether the module DDM parameters have exceeded the threshold value.
Test Data	<pre> switch# show interface eth1/19 transceiver details Ethernet1/19 transceiver is present type is CWDM-1470 name is NADDOD part number is SFP-1G-CW10-1470 revision is A serial number is ACS22060700480 nominal bitrate is 1300 MBit/sec Link length supported for 9/125um fiber is 10 km cisco id is 3 cisco extended id number is 4 SFP Detail Diagnostics Information (internal calibration) ----- Current Alarms Warnings Measurement High Low High Low ----- Temperature 37.42 C 90.00 C -45.00 C 85.00 C -40.00 C Voltage 3.15 V 3.59 V 3.00 V 3.50 V 3.09 V Current 18.52 mA 90.00 mA 1.00 mA 85.00 mA 2.00 mA Tx Power -6.32 dBm -1.99 dBm -10.00 dBm -3.00 dBm -9.03 dBm Rx Power -6.75 dBm -1.99 dBm -26.98 dBm -3.00 dBm -25.22 dBm Transmit Fault Count = 0 ----- </pre>

Note: ++ high-alarm; + high-warning; -- low-alarm; - low-warning

switch# show interface eth1/20 transceiver details

Ethernet1/20

```

transceiver is present
type is CWDM-1470
name is NADDOD
part number is SFP-1G-CW10-1470
revision is A
serial number is ACS22060700481
nominal bitrate is 1300 MBit/sec
Link length supported for 9/125um fiber is 10 km
cisco id is 3
cisco extended id number is 4
    
```

SFP Detail Diagnostics Information (internal calibration)

	Current Measurement	Alarms		Warnings	
		High	Low	High	Low
Temperature	37.36 C	90.00 C	-45.00 C	85.00 C	-40.00 C
Voltage	3.27 V	3.59 V	3.00 V	3.50 V	3.09 V
Current	18.68 mA	90.00 mA	1.00 mA	85.00 mA	2.00 mA
Tx Power	-6.49 dBm	-1.99 dBm	-10.00 dBm	-3.00 dBm	-9.03 dBm
Rx Power	-6.88 dBm	-1.99 dBm	-26.98 dBm	-3.00 dBm	-25.22 dBm
Transmit Fault Count = 0					

Note: ++ high-alarm; + high-warning; -- low-alarm; - low-warning

SFP-1G-CW10-1470		
Vendor	NADDOD	NADDOD
Part Number	SFP-1G-CW10-1470	SFP-1G-CW10-1470
Serial Number	ACS22060700480	ACS22060700481
Wavelength	1470nm	1470nm
Link Length	10km	10km
Transceiver Type	CWDM-1470	CWDM-1470
DDM Alarm	NO	NO

	DDM-Temp	37.42°C	37.36°C
	DDM-Voltage	3.15V	3.27V
	DDM-Tx Bias Current	18.52mA	18.68mA
	DDM-Tx Power	-6.32dBm	-6.49dBm
	DDM-Rx Power	-6.75dBm	-6.88dBm
Test Conclusion	After testing, the above Transceiver on N9K-C93180YC-EX vendor name, part number, serial number, DDM and other information is normally identified, the five DDM parameters do not exceed the level I and II thresholds, and the Transceiver operates normally.		
Remarks	\		

5. Appendix

5.1 Transceiver compatibility testing standards

On the basis of the threshold range, the allowed deviation value should be within the standard range specified by the industry protocol.

Content	Details	Standard
Basic Information	Part Number	The part number read by the device is the same as the Part Number on the label. (If there are special requirements, the actual information shall prevail)
	Serial Number	The serial number read by the device is the same as the serial number on the label. (If there is special requirement, the actual information shall prevail).
	Vendor	The vendor name information read is NADDOD. (If there are special requirements, the actual information shall prevail).
	Transceiver Type	Transceiver information read by the device is consistent with that specified on the actual optics protocol specification (SFF-8636/SFF-8024).
	Wavelength	Transceiver wavelength information read by the device is consistent with the module description.
	Link Length	Transceiver maximum transmission distance information read by the device is consistent with the module description.
DDM Information	Temp	1. The actual DDM information is within the DDM threshold and there are no alarms. 2. The DDM threshold range is in accordance with the module specification.
	Voltage	
	Tx Bias Current	
	Tx Power	
	Rx Power	

Port Information	Port Rate	The data rate information read on the switch port corresponds to the actual rate of the optics.
	Port Status	When the transceiver is connected, the port status information is UP.
	Switch Port LED Status	The port indicators on both ends of the transceiver will be green when the transceiver is connected.
	Port Count	No packet loss, no error code, no CRC, no other ERROR packets.
Device Log		The device does not have any transceiver warning message.

Further Information :

Web www.naddod.com

Email For order requirements: sales@naddod.com

For cooperation: agency@naddod.com

For customer service: support@naddod.com

For other informations: info@naddod.com

For technical support: tech@naddod.com

Disclaimer

1. We are committed to continuous product improvement and feature upgrades, and the contents contained in this manual are subject to change without notice.

2. Nothing herein should be construed as constituting an additional warranty.

3. NADDOD assumes no responsibility for the use or reliability of equipment or software not provided by NADDOD.

Copyright © NADDOD.COM All Rights Reserved, 2022