



OPTICAL TRANSCEIVER TEST REPORT

Tested by: Doubt.Zheng | Date: 2022.12.24

1. Test Purpose

Test objects: SFP-1G-EX-31, Through the corresponding tests, the test parameters conform to the relevant industry standards, and the test transceivers can be used normally in Cisco brand equipment, laying the foundation for the subsequent cooperation with customers.

2. Test items

Test items		Test details
Compatibility Testing	Connectivity testing	The transceiver can connect both ends of the device normally, and the device port status is up.
	Parameter testing	The transceiver PN, VN, SN, and DDM information read by the device is consistent with the module tag description.

3. Test environment

3.1. Test samples

Vendor Name	Part Number	Serial Number	Transceiver Description
NADDOD	SFP-1G-EX-31	ACS22060700050	1000BASE-EX SFP 1310nm 40km DOM LC Transceiver SMF Module
NADDOD	SFP-1G-EX-31	ACS22060700051	1000BASE-EX SFP 1310nm 40km DOM LC Transceiver SMF Module

3.2. Test equipment

Equipment Brand	Equipment Model	Software version (running)
Cisco	Cisco Nexus N9K-C93180YC-EX	NXOS: version 9.2(3)

4. Test data

4.1. Connectivity testing

Test Method	<ol style="list-style-type: none"> check whether the device status is normal.; Check whether the port device port LED is green; (individual brand port LED is yellow or white) check whether the device port is normally linked up; Check whether the device port rate is up to standard.
-------------	---

Test Data	<pre> switch# sh ver Cisco Nexus Operating System (NX-OS) Software TAC support: http://www.cisco.com/tac Copyright (C) 2002-2019, Cisco and/or its affiliates. All rights reserved. The copyrights to certain works contained in this software are owned by other third parties and used and distributed under their own licenses, such as open source. This software is provided "as is," and unless otherwise stated, there is no warranty, express or implied, including but not limited to warranties of merchantability and fitness for a particular purpose. Certain components of this software are licensed under the GNU General Public License (GPL) version 2.0 or GNU General Public License (GPL) version 3.0 or the GNU Lesser General Public License (LGPL) Version 2.1 or Lesser General Public License (LGPL) Version 2.0. A copy of each such license is available at http://www.opensource.org/licenses/gpl-2.0.php and http://opensource.org/licenses/gpl-3.0.html and http://www.opensource.org/licenses/lgpl-2.1.php and http://www.gnu.org/licenses/old-licenses/library.txt. Software BIOS: version 07.59 NXOS: version 9.2(3) BIOS compile time: 08/26/2016 NXOS image file is: bootflash:///nxos.9.2.3.bin NXOS compile time: 2/17/2019 5:00:00 [02/17/2019 15:07:27] Hardware cisco Nexus9000 93180YC-EX chassis Intel(R) Xeon(R) CPU @ 1.80GHz with 24632676 kB of memory. Processor Board ID FD021192HKE Device name: switch bootflash: 53298520 kB Kernel uptime is 0 day(s), 0 hour(s), 33 minute(s), 19 second(s) Last reset at 447487 usecs after Mon Apr 26 06:08:11 2021 Reason: Module PowerCycled System version: Service: HW check by card-client plugin Core Plugin, Ethernet Plugin </pre>
-----------	--

	<div>Active Package(s):</div> <div>switch# sh inv</div> <div>NAME: "Chassis", DESCR: "Nexus9000 93180YC-EX chassis"</div> <div>PID: N9K-C93180YC-EX , VID: V01 , SN: FDO21192HKE</div> <div>NAME: "Slot 1", DESCR: "48x10/25G + 6x40/100G Ethernet Module"</div> <div>PID: N9K-C93180YC-EX , VID: V01 , SN: FDO21192HKE</div> <div>NAME: "Power Supply 1", DESCR: "Nexus9000 93180YC-EX chassis Power Supply"</div> <div>PID: NXA-PAC-650W-PE , VID: V02 , SN: LIT21182CKL</div> <div>NAME: "Power Supply 2", DESCR: "Nexus9000 93180YC-EX chassis Power Supply"</div> <div>PID: NXA-PAC-650W-PE , VID: V02 , SN: LIT21182G55</div> <div>NAME: "Fan 1", DESCR: "Nexus9000 93180YC-EX chassis Fan Module"</div> <div>PID: NXA-FAN-30CFM-F , VID: V01 , SN: N/A</div> <div>NAME: "Fan 2", DESCR: "Nexus9000 93180YC-EX chassis Fan Module"</div> <div>PID: NXA-FAN-30CFM-F , VID: V01 , SN: N/A</div> <div>NAME: "Fan 3", DESCR: "Nexus9000 93180YC-EX chassis Fan Module"</div> <div>PID: NXA-FAN-30CFM-F , VID: V01 , SN: N/A</div> <div>NAME: "Fan 4", DESCR: "Nexus9000 93180YC-EX chassis Fan Module"</div> <div>PID: NXA-FAN-30CFM-F , VID: V01 , SN: N/A</div> <div>switch# sh int eth 1/14-16 stat</div> <div><div>-----</div><table><tr><th>Port</th><th>Name</th><th>Status</th><th>Vlan</th><th>Duplex</th><th>Speed</th><th>Type</th></tr><tr><td>Eth1/14</td><td>--</td><td>connected</td><td>routed</td><td>full</td><td>1000</td><td>1000base-EX</td></tr><tr><td>Eth1/15</td><td>--</td><td>xcvrAbsen</td><td>routed</td><td>auto</td><td>auto</td><td>--</td></tr><tr><td>Eth1/16</td><td>--</td><td>connected</td><td>routed</td><td>full</td><td>1000</td><td>1000base-EX</td></tr></table><div>-----</div></div>	Port	Name	Status	Vlan	Duplex	Speed	Type	Eth1/14	--	connected	routed	full	1000	1000base-EX	Eth1/15	--	xcvrAbsen	routed	auto	auto	--	Eth1/16	--	connected	routed	full	1000	1000base-EX
Port	Name	Status	Vlan	Duplex	Speed	Type																							
Eth1/14	--	connected	routed	full	1000	1000base-EX																							
Eth1/15	--	xcvrAbsen	routed	auto	auto	--																							
Eth1/16	--	connected	routed	full	1000	1000base-EX																							
Test Situation	SFP-1G-EX-31																												
	Port Number	Eth1/14			Eth1/16																								
	Port Status	connected			connected																								
	Port Link Rate	1G			1G																								
Test Conclusion	After testing, the above transceivers are normally connected on Cisco Nexus N9K-C93180YC-EX, the device port LEDs at both ends are always on white, the link is linkup.																												

Remarks	
---------	--

4.2. Parameter Testing

Test Method	<div>1. check whether the basic information such as module manufacturer name, model name and serial number is correct.</div> <div>2. check whether the module transmission distance, wavelength, type and other key parameters are correct.</div> <div>3. check whether the module DDM parameters have exceeded the threshold value.</div>
Test Data	<div>switch# sh int eth 1/14-16 tran det</div> <div>Ethernet1/14</div> <div>transceiver is present</div> <div>type is 1000base-EX</div> <div>name is NADDOD</div> <div>part number is SFP-1G-EX-31</div> <div>revision is A0</div> <div>serial number is ACS22060700050</div> <div>nominal bitrate is 1300 MBit/sec</div> <div>Link length supported for 9/125um fiber is 40 km</div> <div>cisco id is 3</div> <div>cisco extended id number is 4</div> <div>SFP Detail Diagnostics Information (internal calibration)</div> <div><div><div></div><div>Current</div><div>Measurement</div></div><div><div></div><div>Alarms</div><div>HighLow</div></div><div><div></div><div>Warnings</div><div>HighLow</div></div></div> <div><div>Temperature</div><div>25.39 C</div><div>90.00 C</div><div>-45.00 C</div><div>85.00 C</div><div>-40.00 C</div></div> <div><div>Voltage</div><div>3.26 V</div><div>3.59 V</div><div>3.00 V</div><div>3.50 V</div><div>3.09 V</div></div> <div><div>Current</div><div>19.34 mA</div><div>90.00 mA</div><div>1.00 mA</div><div>85.00 mA</div><div>2.00 mA</div></div> <div><div>Tx Power</div><div>-6.28 dBm</div><div>-1.99 dBm</div><div>-10.00 dBm</div><div>-3.00 dBm</div><div>-9.03 dBm</div></div> <div><div>Rx Power</div><div>-6.12 dBm</div><div>-1.99 dBm</div><div>-26.98 dBm</div><div>-3.00 dBm</div><div>-25.22 dBm</div></div> <div><div>Transmit Fault Count = 0</div></div> <div>Note: ++ high-alarm; + high-warning; -- low-alarm; - low-warning</div> <div>Ethernet1/15</div> <div>transceiver is not present</div> <div>Ethernet1/16</div> <div>transceiver is present</div> <div>type is 1000base-EX</div> <div>name is NADDOD</div> <div>part number is SFP-1G-EX-31</div>

revision is A0
 serial number is ACS22060700051
 nominal bitrate is 1300 MBit/sec
 Link length supported for 9/125um fiber is 40 km
 cisco id is 3
 cisco extended id number is 4

SFP Detail Diagnostics Information (internal calibration)

	Current	Alarms		Warnings	
	Measurement	High	Low	High	Low
Temperature	26.47 C	90.00 C	-45.00 C	85.00 C	-40.00 C
Voltage	3.31 V	3.59 V	3.00 V	3.50 V	3.09 V
Current	17.15 mA	90.00 mA	1.00 mA	85.00 mA	2.00 mA
Tx Power	-6.42 dBm	-1.99 dBm	-10.00 dBm	-3.00 dBm	-9.03 dBm
Rx Power	-6.05 dBm	-1.99 dBm	-26.98 dBm	-3.00 dBm	-25.22 dBm
Transmit Fault Count = 0					

Note: ++ high-alarm; + high-warning; -- low-alarm; - low-warning

Test
situation

SFP-1G-EX-31		
Vendor	NADDOD	NADDOD
Part Number	SFP-1G-EX-31	SFP-1G-EX-31
Serial Number	ACS22060700050	ACS22060700051
Wavelength	/	/
Link Length	40km	40km
Transceiver Type	1000base-EX	1000base-EX
DDM Alarm	NO	NO
DDM-Temp	25.39°C	26.47°C
DDM-Voltage	3.26V	3.31V
DDM-Tx Bias Current	19.34mA	17.15mA
DDM-Tx Power	-6.28dBm	-6.42dBm

	DDM-Rx Power	-6.12dBm	-6.05dBm
Test Conclusion	After testing, the above Transceiver on Cisco Nexus N9K-C93180YC-EX vendor name, part number, serial number, DDM and other information is normally identified, the five DDM parameters do not exceed the level I and II thresholds, and the Transceiver operates normally.		
Remarks	1.Cisco Nexus series devices cannot read optical module bands.		

5.Appendix

5.1 Transceiver compatibility testing standards

On the basis of the threshold range, the allowed deviation value should be within the standard range specified by the industry protocol.

Content	Details	Standard
Basic Information	Part Number	The part number read by the device is the same as the Part Number on the label. (If there are special requirements, the actual information shall prevail)
	Serial Number	The serial number read by the device is the same as the serial number on the label.(If there is special requirement, the actual information shall prevail).
	Vendor	The vendor name information read is NADDOD.(If there are special requirements, the actual information shall prevail).
	Transceiver Type	Transceiver information read by the device is consistent with that specified on the actual optics protocol specification (SFF-8636/SFF-8024).
	Wavelength	Transceiver wavelength information read by the device is consistent with the module description.
	Link Length	Transceiver maximum transmission distance information read by the device is consistent with the module description.
DDM Information	Temp	1. The actual DDM information is within the DDM threshold and there are no alarms. 2. The DDM threshold range is in accordance with the module specification.
	Voltage	
	Tx Bias Current	
	Tx Power	
	Rx Power	
Port Information	Port Rate	The data rate information read on the switch port corresponds to the actual rate of the optics.
	Port Status	When the transceiver is connected, the port status information is UP.
	Switch Port LED Status	The port indicators on both ends of the transceiver will be green when the transceiver is connected.

	Port Count	No packet loss, no error code, no CRC, no other ERROR packets.
Device Log		The device does not have any transceiver warning message.

Further Information :

Web www.naddod.com

Email For order requirements: sales@naddod.com

For cooperation: agency@naddod.com

For customer service: support@naddod.com

For other informations: info@naddod.com

For technical support: tech@naddod.com

Disclaimer

1. We are committed to continuous product improvement and feature upgrades, and the contents contained in this manual are subject to change without notice.

2. Nothing herein should be construed as constituting an additional warranty.

3. NADDOD assumes no responsibility for the use or reliability of equipment or software not provided by NADDOD.

Copyright © NADDOD.COM All Rights Reserved, 2022