

10G DWDM XFP 80km Optical Transceiver

Features

- Support multi protocol from 9.95Gb/s to 11.3Gb/s
- Hot pluggable 30 pin connector
- Compliant with XFP MSA
- Transmission distance of 80km over single mode fiber
- DWDM EML laser transmitter
- APD Receiver
- 100GHz ITU Grid, C Band
- Duplex LC connector
- 2-wire interface for management and diagnostic monitor
- XFI electrical interface with AC coupling
- Power supply voltages : +3.3V, +5V
- Temperature range: 0°C to 70°C
- Power dissipation: <1.5W
- ROHS Compliant

Applications

- DWDM Networks
- SONET OC-192 /SDH STM-64
- 80km 10G FC
- 10GBASE-ZR/ZW Ethernet

Compliance

- IEEE 802.3ae 10GBASE-ZR
- XFP MSA

Description

The XFP-10G-DW80 transceivers are compliant with the current XFP Multi-Source Agreement (MSA) Specification. The high performance cooled DWDM EML transmitter and high sensitivity APD receiver provide superior performance for SONET/SDH and Ethernet applications up to 80km optical links.

Absolute Maximum Ratings

Table1-Absolute Maximum Ratings				
Parameter	Symbol	Min.	Max.	Unit
Storage Temperature Range	T _{ST}	-40	85	°C
Supply Voltage 1	VCC	-0.5	4.0	V
Supply Voltage 2	VCC	-0.5	6.0	V

Recommended Operating Environment

Table2-Recommended Operating Environment					
Parameter	Symbol	Min.	Typical	Max.	Unit
Operating Temperature Range	T _{ip}	0		70	°C
Power Supply Voltage	VCC	3.13	3.3	3.45	V
Bit Rate	BR	9.95		11.3	Gb/s
Bit Error Rate	BER			10 ⁻¹²	
Max. Supported Link Length	L			80	km

Optical Characteristics

Table3-Optical Characteristics						
Parameter	Symbol	Min.	Typical	Max.	Unit	Notes
Transmitter						
Data Rate	B	9.95		11.3	Gbps	
Maximum Launch Power	P _{max}	-1		4	dBm	1
Optical Wavelength-End Of Life	λ	X-100	X	X+100	nm	
Optical Wavelength-Beginning Of Life	λ	X-25	X	X+25	nm	
Spectral Width@-20dB	Δλ			1	nm	
Side Mode Suppression Ratio	SMSR _{min}	30			dB	
Average Launch Power of OFF Transmitter	P _{OFF}			-30	dBm	
Extinction Ratio	ER	8.2			dB	

Rise/Fall Time (20%~80%)		T _r /T _f		35	ps	
Tx Jitter		T _{xj}	Compliant with each standard requirements			
Optical Eye Mask			IEEE802.3ae			2
Receiver						
Data Rate		BR	9.95		11.3	Gbps
Center Wavelength		λ _c	1260		1600	nm
Receiver Sensitivity		RSEN			-24	dBm
Maximum Input Power		P _{MAX}	-7			dBm
Receiver Reflectance		R _{rx}			-27	dB
LOS	Optical Assert	LOS _A	-34			dBm
	Optical Dessert	LOS _D			-24	dBm
LOS Hysteresis		LOS _H	0.5		5	dB

Notes:

[1] The optical power is launched into SMF.

[2] Measured with a PRBS 2₃₁-1 test pattern @10.3125Gbps BER< 10⁻¹².

Electrical Characteristics

Table4-Electrical Characteristics

Parameter	Symbol	Min.	Typical	Max.	Unit	Notes
Supply Voltage 1	VCC5	4.75		5.25	V	
Supply Voltage 2	VCC3	3.13		3.45	V	
Supply Current – Vcc5 supply	I _{CC5}			200	mA	
Supply Current – Vcc3 supply	I _{CC3}			550	mA	
Module Total Power	P			3.5	W	
Transmitter						
Input Differential Impedance	R _{IN}		100		Ω	1
Differential Data Input Swing	V _{IN,pp}	150		820	mV	
Transmit Disable Voltage	V _D	2		VCC	V	
Transmit Enable Voltage	V _{EN}	GND		GND+0.8	V	
Transmit Disable Assert Time	T _{off}			100	ms	
Tx Enable Assert Time	T _{on}			100	ms	
Receiver						
Differential Data Output Swing	V _{out,pp}	300	500	850	mV	
Output Rise Time	t _{RISE}			35	ps	2
Output Fall Time	t _{FALL}			35	ps	2
LOS Fault	V _{LOSFT}	VCC – 0.5		VCC _{HOST}	V	3
LOS Normal	V _{LOSNR}	GND		GND+0.5	V	3
Power Supply Rejection	PSR	See Note 4 below				4

Notes:


[1] After internal AC coupling.

[2] 20-80%.

[3] Loss of Signal is open collector to be pulled up with a 4.7k – 10kohm resistor to 3.15 – 3.6V. Logic 0 indicates normal operation; logic 1 indicates no signal detected.

[4] Per Section 2.7.1. in the XFP MSA Specification.

Pin Description



Pin Function Definitions

Table5-Pin Function Definitions				
Pin Number	Logic	Symbol	Name/Description	Notes
1		GND	Module Ground	1
2		VEE5	Optional -5.2 Power Supply – Not required	
3	LVTTL-I	Mod-Desel	Module De-select; When held low allows the module to respond to 2-wire serial interface commands	
4	LVTTL-O	Interrupt	Interrupt (bar); Indicates presence of an important condition which can be read over the serial 2-wire interface	2
5	LVTTL-I	TX_DIS	Transmitter Disable; Transmitter laser source turned off	
6		VCC5	+5 Power Supply	
7		GND	Module Ground	1
8		VCC3	+3.3V Power Supply	
9		VCC3	+3.3V Power Supply	
10	LVTTL-I	SCL	Serial 2-wire interface clock	2
11	LVTTL-I/O	SDA	Serial 2-wire interface data line	2
12	LVTTL-O	Mod_Abs	Module Absent; Indicates module is not present. Grounded in the module	2
13	LVTTL-O	Mod_NR	Module Not Ready	2
14	LVTTL-O	RX_LOS	Receiver Loss of Signal indicator	2
15		GND	Module Ground	1
16		GND	Module Ground	1
17	CML-O	RD-	Receiver inverted data output	
18	CML-O	RD+	Receiver non-inverted data output	
19		GND	Module Ground	1
20		VCC2	+1.8V Power Supply – Not required	
21	LVTTL-I	P_Down/RST	Power Down; When high, places the module in the low power stand-by mode and on the falling edge of P_Down initiates a module reset Reset; The falling edge initiates a complete reset of the module including the 2-wire serial interface, equivalent to a power cycle	
22		VCC2	+1.8V Power Supply – Not required	
23		GND	Module Ground	1
24	PECL-I	RefCLK+	Reference Clock non-inverted input, AC coupled on the host board – Not required	3
25	PECL-I	RefCLK-	Reference Clock inverted input, AC coupled on the host board –Not required	3
26		GND	Module Ground	1
27		GND	Module Ground	1
28	CML-I	TD-	Transmitter inverted data input	
29	CML-I	TD+	Transmitter non-inverted data input	
30		GND	Module Ground	1

Notes:

- [1] Module circuit ground is isolated from module chassis ground within the module
- [2] Open collector; should be pulled up with 4.7k – 10k ohms on host board to a voltage between 3.15V and 3.6V.
- [3] A Reference Clock input is not required.

Typical Application Circuit






Diagram Mechanical Drawing



Further Information:

Web www.naddod.com

Email For order requirements: sales@naddod.com
For customer service: support@naddod.com
For technical support: tech@naddod.com

For cooperation: agency@naddod.com

For other informations: info@naddod.com

Disclaimer

1. We are committed to continuous product improvement and feature upgrades, and the contents contained in this manual are subject to change without notice.
 2. Nothing herein should be construed as constituting an additional warranty.
 3. NADDOD assumes no responsibility for the use or reliability of equipment or software not provided by NADDOD.
- Copyright © NADDOD.COM All Rights Reserved, 2022